

Mechanical Control of Fluids in Micro-Analytical Devices

Field of the Invention

5 This invention relates to an apparatus and method for manipulating fluid samples.

Background to the Invention

10 Miniaturization of analytical systems has played an important role in the development of fast analysis systems using very small amounts of sample. During the last decade, intensive efforts have been devoted to the design of whole laboratory systems on micro-analytical
15 substrates as analytical tools, utilising for example, capillary electrophoresis and liquid chromatography. However, developments in microanalysis have been hindered to some extent by the lack of efficient fluid pumping systems. Fluid movement in micro-channel networks formed
20 in glass, silica or polymeric substrates is conventionally driven by capillary flow or electro-osmotic pumping. The former process relies on chemical modifications of the surface properties of the micro-analytical substrate, which in turn establish
25 restrictions on the flow direction and rate. The latter process involves high-voltage inputs through electrodes in contact with a solution, which is usually referred to as electrokinetic pumping.

30 A critical parameter in performing high-resolution electrophoresis or electrochromatography is the injection. In standard capillary electrophoresis two injection methods are generally used. The first method,

electrokinetic injection, is easy to perform and requires placing the capillary in contact with a sample solution and pumping the latter inside the capillary by applying a high voltage. However, this injection method is not
5 always suitable as in the case where some of the species in the sample to be analysed have very different electrophoretic mobilities. In this case some of the species will migrate during the injection, resulting in bias in the final concentration ratio between the
10 analytes. For instance, the injection of a sample in pure water in order to generate a strong stacking effect is very difficult using this method. Also, the injection of very complex mixtures, for example samples of high protein concentration, is difficult, because the proteins
15 may change the zeta potential in the sample channel resulting in instability in the flow intensity or even in the electro-osmotic flow direction. Several injection patterns based on electrically driven flow have been proposed such as T-injection, double-T-injection as well
20 as electrically pinched injection as exemplified in U.S. Patent Nos. 5,858,195; 6,001,229; 6,010,607; 6,010,608; and 6,033,546. All of these inventions were linked to the application of a high voltage facilitating pumping of the sample solution. Several potentials can be applied in
25 different channels of the device in order to force the solution to flow producing well defined sample plugs. The principal drawback of the inventions described is the necessity to work with samples which have well-defined conductivity, viscosity and thermal properties.
30 Therefore, analyses of other samples has to be performed using the second method of injection, pressure driven injection, which is less sensitive to sample composition.

Summary of the Invention

The present invention relates to an apparatus and method of use thereof for performing fluid manipulations in micro-analytical laboratory systems for a large variety of applications, including sample injection. The invention allows precise control of fluid transport in micro-fabricated systems for performing chemical and biochemical analyses, syntheses and detection.

The method of the invention combines a multi-port valve to control the pressure in a network of micro-channels with mechanical pumping of a fluid to provide low cost analytical devices that can be coupled to conventional separation and/or detection systems that find broad applications in the fields of chemistry, biochemistry, biotechnology, molecular biology and numerous other fields.

The system can be used as a pressure injector facilitating separation by means of chromatography, electrophoresis or electrochromatography in micro-analytical systems. The present invention comprises a new method for pumping, injecting and driving fluids by employing a multi-port injection valve to control the pressure in portions of a micro-channel network and a mechanical pump to introduce fluids in said portions.

The device is composed of interconnected covered channels connected with tubes to an external multi-port injection valve. The multi-port injection valve controls the direction of the flow within the different sections of the device. The system can be used to prepare a sample

plug by pressure to perform chromatography, electrochromatography and/or electrophoresis. The sample solution can be an aqueous or an organic solution, and can contain dissolved species such as one or more salts.

5 The invention is not limited by the concentration, conductivity or thermal properties of the sample.

The present invention relates to a micro-analytical apparatus for manipulating fluid samples, comprising a

10 substrate having at least a first and second covered channel with openings at either end of said first and second channel, said first and second covered channels intersecting to form a common intersection, characterized in that at least three of the openings to said first and

15 second covered channels are connected to a multi-port valve to control the pressure in the channels.

The substrate of the invention is preferably made of a substance selected from the following materials: glass,

20 silicon, ceramic, organic polymers, a metallic material or mixtures thereof. Other suitable substances will be apparent to those skilled in the art.

Preferably, the channels in the substrate are

25 covered by lamination, thermal bonding, anodic bonding, electrostatic interaction, pressure or a combination thereof.

In an embodiment of the invention all of the

30 openings at either end of the first and second covered channels are connected to the multi-port valve.

In a further embodiment of the invention the first or second covered channel contains a detection region.

In a preferred embodiment of the invention the
5 detection region consists of electrodes, or a window for spectroscopic detection.

In an alternative embodiment of the invention the first or second covered channel is connected to a
10 detection device.

The apparatus according to the present invention can be used in a method of manipulating fluid samples by:

- 15 a. mechanically pumping an eluent solution into one end of the first covered channel and through the intersection whilst applying pressure to either end of the second covered channel when the multi-port valve is in a first position;
- 20 b. then switching the multi-port valve to a second position so that a sample solution is pumped into one end of the second covered channel whilst pressure is applied at the other three openings; and
- 25 c. switching the multi-port valve back to the first position so that the sample is pushed from one arm of the second covered channel of the device into the intersection and along the first channel.

Alternatively, the apparatus of the invention can be
30 employed when an electrical field is applied in a portion of said first or second channel in order to sustain or stop the flow of liquid during the injection step.

In an alternative embodiment of the method of the invention pressure is applied only during the injection step.

5 In a still further embodiment of the invention the sample is pushed from one arm of the second covered channel into the intersection and along the first covered channel of the device by means of electrophoresis, electro-osmosis or the like.

10 Alternatively, at least part of the first or second covered channel contains a stationary phase in order to perform chromatography, electrochemistry, electrophoresis, immunological or enzymatic analysis or
15 any combination thereof.

The term stationary phase refers to any chemical or biological compound immobilized (for instance by physi- or chemi-sorption, by ionic or covalent binding) onto a
20 wall of said covered micro-channel or onto the surface of a packing material like beads filling said covered micro-channel.

Brief Description of the Drawings

25 The invention will now be described in more detail, by way of example only, with reference to the accompanying drawings, in which:-

30 Figure 1(a) and 1(b) are schematic diagrams of a polymer micro-analytical device according to two alternative embodiments of the invention;

Figures 2 (a), (b) and (c) are schematic diagrams of a two-way micro-8-port valve connected to a micro-channel network similar to that shown in Figure 1;

5 Figure 3 is a chromatogram obtained by amperometric measurement following injection of hexacyanoferrate into the apparatus shown in Figure 2;

10 Figure 4 is a chromatogram showing the results of the reproducibility test of the injection in the configuration presented in Figure 2;

15 Figure 5(a) shows a configuration of the pressure pinched injection;

 Figure 5(b) shows a configuration of the separation position;

20 Figure 6 is a photograph showing the fluorescent image of the intersection during pressure pumping under the configuration presented in figure 5(a);

25 Figure 7 is a sequence of photographs showing the position of the plug when injected into a channel as shown in Fig. 5(a) and when the device is then changed to the configuration shown in Fig. 5(b); and

 Figure 8 is a chromatogram of the injected plugs in the configuration presented in Fig. 5.

Detailed Description of the Invention

Example 1

5 A micro-channel network on a polymer substrate (e.g. polyethylene terephthalate (PET)) was fabricated by the use of UV Excimer laser photoablation. A schematic diagram of the analytical micro-analytical device is shown in Figure 1. The device comprises an injector, a
10 separation column and a detector 8. The injection part is composed of an intersection 3 between two side micro-channels 1, 2 perpendicularly photoablated to the main channel. The channels are then covered by lamination forming a set of capillaries.

15 The structure shown in Fig. 1(a) is composed of an asymmetrical cross of covered microchannels 1, 2 that can be connected to external tubes at positions 4, 5, 6 and 7. In the longer channel 1 (5cm), a conductivity detector
20 8 can be inserted to detect the injected plugs. The structure shown in Fig. 1(b) is composed of four channels 4-3, 5-3, 6-3 and 7-3 of equal length (1.1cm) with symmetrical arms that can contain electrodes 8 for detection or for voltage application purposes.

25

Example 2

Simple Switch

30 Figures 2(a), (b) and (c) illustrate how a sample can be injected in a micro-channel network of the present invention.

Four inlet reservoirs of the micro-channel network 4, 5, 6 and 7 were connected to a two-way micro-8-port valve with the configuration shown in Fig. 2(a) allowing injection and elution of the sample. The 8-port micro-valve was connected to syringe pumps with a flow rate range of between 0.01 to 1000 $\mu\text{l}\cdot\text{h}^{-1}$ which are connected to the micro-channel.

The first method necessitates the use of two solutions (running buffer and sample solution) that are pumped independently inside the structure. On one position of the valve (see Figure 2 (a)) the running buffer is pumped from one inlet 5 to one outlet 7 whereas both side arms 4-3, 6-3 of the structures are connected together as a loop. In this case, the running solution is pumped linearly throughout the structure. At a given time, the multiport valve is switched to the second position represented by Figure 2(b), where the sample enters from side arm 4-3, whereas this time no flow is entering the main channel 1. During this time, a plug is formed at the intersection 3. The multiport valve is then placed on the first position (Fig. 2a), where the running buffer drives the sample in the intersection 3 into the main channel 1 towards the outlet 7 or a detector.

Figures 2 (a), (b) and (c) are schematic diagrams showing a two-way micro-8-port valve connected to a micro-channel network similar to those shown in Figure 1, which defines the movement of a sample and an elution solution as a function of the position of the valve. Figures 2(a), (b) and (c) illustrate how a sample can be injected into the micro-channel network of the invention.

A) The micro-8-port valve is put into Position A, which corresponds to port 1a connected to port 8a, 2a to 3a, 4a to 5a, and 6a to 7a. In this configuration, the eluent flows from port 2a into the main channel 1 and then out to port 1a, whereas the sample does not flow within the micro-channel network; the pressure is maintained constant in the sample branch 2 of the micro-channel network since the loop of ports 6a and 7a is closed.

B) Then the micro-8-port valve is put into Position B which corresponds to port 1a connected to port 2a, 3a to 4a, 5a to 6a, and 7a to 8a. In this configuration, the eluent does not flow within the micro-channel network, whereas the sample solution flows from port 6a into the sample channel 2 and then out to port 7a. The pressure is maintained constant in the main channel 1 of the micro-channel network since the loop of ports 1a and 2a is closed. During this procedure a plug is formed at the intersection.

C) The micro-8-port valve is then put back to Position A. As a result, the eluent pushes the sample plug into the main channel 1 towards the channel outlet 7 or a detector 8.

It is clear from the arrangement described in A and C above that the connections between ports 1a and 2a and the connection between ports 6a and 7a can be blocked without affecting the injection and separation pattern.

To illustrate the simple switch method experimental data relating to the oxidation of 10 mM of hexacyanoferrate measured by amperometric detection are shown in Figure 3. (800 mV was applied between two electrodes placed facing each other in the microchannel). The sharp lines on the chromatogram occur as a result of the switch of the multiport valve from position A to position B. The simple switch method allows very accurate control of the injection or of the separation sequences. In this example the injected peak reached the detector about 10 seconds after the switch, whereas the plug was formed in about 15 seconds. The shape of the detected peak is Gaussian which indicates convective flow of the solution. In order to test the reproducibility of the injection pattern, other experiments were performed by varying the injection time. The results obtained from these experiments are shown in Figure 4 where A-B indicates the switch from position A to position B of the microport valve and B-A indicates the switch from position B to position A of the microport valve. These results indicate that the shape and the retention time of the injected plug depend on the injection time. This irreproducibility is probably due to sample diffusion or compression along the main channel, meaning that the sample plug will not be well controlled under such conditions. However, such variations can be resolved by controlling the flow rate in the connection tubes by for example connecting them to tubes or capillaries of different dimensions or working with different flow rates.

Example 3Pressure Pinched Switch

5 In order to eliminate the time dependence of the sample plug size during the injection, it is possible to force running buffer along both sides of the sample flow. This system is similar to the pinched injection method invented by Ramsey and described in U.S. Patent No. 10 6,033,546, which is controlled by electrically driven flow for performing microfluidic manipulation. Indeed, in both cases, the sample solution is pumped through the intersection whilst two concurrent flows are pinching it from the side. This means that the sample solution has no time to diffuse inside the main channel and the injection 15 plug volume is independent of the duration of the injection. The fundamental difference of the present invention is that no electrical field is necessary inside the structure in order to pump the solution. Therefore, 20 the present device can be used for the manipulation of solutions that do not contain salt or contain very complex mixtures of solute molecules, including high concentrations of charged species. To achieve this goal, the tubes must be connected in a different way to the 25 structure through the multi-port valve.

First, the running buffer must be connected directly to the structure, without going through the multi-port valve as presented in Figure 5. This means that the same 30 pressure is applied to inlet 5 during the injection as well as during the separation. The other tubes are connected as presented in Figure 5(a), where a pressure is applied from three channel openings 4, 5 and 7 towards

the intersection 3 and where one single channel opening 6 is connected to the waste. The pressure in the channels can be adjusted to get a symmetric or an asymmetric injection pattern that will generate a bigger or a smaller plug. In this regard the size of the syringes 9 can be the same or of different sizes in order to obtain a symmetrical or an asymmetrical triangle shape. When the multi-port valve is switched to the position shown in Figure 5(b), the running buffer direction is linear and brings a plug 10 with it through the main channel 1. The channel openings 4 and 6 are connected together and therefore, the net flow in the second channel 2 is very low. Compression of the solution induces a push back effect in the second channel 2, allowing the injection of a small and very well defined plug 10. The solution is then pushed and the plug 10 transforms to a parabolic shape with respect to the flow rate. This type of injection is suited to any kind of solution and is not limited to the conductivity or surface properties of the material used for the structure.

Example 4

In order to demonstrate the concept, the intersection of the channels was placed under a microscope and fluorescence and/or visible images were taken at different times during the injection or separation pattern. The picture presented in Figure 6 clearly demonstrates the injection pattern shown in Figure 5(a) when a fluorescent solution of 0.1 mM Fluorescein in 10 mM phosphate buffer at pH 7.4 was compressed between two side solutions that are not fluorescent.

Figure 7(a) corresponds to the configuration shown in Fig. 5(a) when the compression is not symmetrical, meaning that the flow rate is not equivalent in different channel sections. The sequence of images shown in Figure 7(b) shows the behaviour of the flow at the intersection when the multi-port valve is switched from the position shown in Figure 5(a) to that shown in 5(b). The plug evolves in a parabolic shape and is then injected into the main channel 1 for separation.

Example 5

To demonstrate the reproducibility of the two sequential injections shown in Figures 5a and 5b a solution of 10 mM Eosine B and 2 mM of sodium chloride was injected into the channel whilst the other flows were composed of pure water. Detection was performed by measuring the conductivity between electrodes inserted facing each other at the end of the channel. A chromatogram showing the results obtained is presented in Figure 8.

The present injection pattern could be used with different solutions such as organic solvents, solutions containing salts or not containing salts as well as with a gradient elution prepared in the tubes. This is an important point when performing any kind of chromatography. This point is also a very important difference from the standard electrokinetic sample manipulations.

5

1972	1973	1974	1975	1976	1977	1978	1979	1980	1981	1982	1983	1984	1985	1986	1987	1988	1989	1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	2101	2102	2103	2104	2105	2106	2107	2108	2109	2110	2111	2112	2113	2114	2115	2116	2117	2118	2119	2120	2121	2122	2123	2124	2125	2126	2127	2128	2129	2130	2131	2132	2133	2134	2135	2136	2137	2138	2139	2140	2141	2142	2143	2144	2145	2146	2147	2148	2149	2150	2151	2152	2153	2154	2155	2156	2157	2158	2159	2160	2161	2162	2163	2164	2165	2166	2167	2168	2169	2170	2171	2172	2173	2174	2175	2176	2177	2178	2179	2180	2181	2182	2183	2184	2185	2186	2187	2188	2189	2190	2191	2192	2193	2194	2195	2196	2197	2198	2199	2200	2201	2202	2203	2204	2205	2206	2207	2208	2209	2210	2211	2212	2213	2214	2215	2216	2217	2218	2219	2220	2221	2222	2223	2224	2225	2226	2227	2228	2229	2230	2231	2232	2233	2234	2235	2236	2237	2238	2239	2240	2241	2242	2243	2244	2245	2246	2247	2248	2249	2250	2251	2252	2253	2254	2255	2256	2257	2258	2259	2260	2261	2262	2263	2264	2265	2266	2267	2268	2269	2270	2271	2272	2273	2274	2275	2276	2277	2278	2279	2280	2281	2282	2283	2284	2285	2286	2287	2288	2289	2290	2291	2292	2293	2294	2295	2296	2297	2298	2299	2300	2301	2302	2303	2304	2305	2306	2307	2308	2309	2310	2311	2312	2313	2314	2315	2316	2317	2318	2319	2320	2321	2322	2323	2324	2325	2326	2327	2328	2329	2330	2331	2332	2333	2334	2335	2336	2337	2338	2339	2340	2341	2342	2343	2344	2345	2346	2347	2348	2349	2350	2351	2352	2353	2354	2355	2356	2357	2358	2359	2360	2361	2362	2363	2364	2365	2366	2367	2368	2369	2370	2371	2372	2373	2374	2375	2376	2377	2378	2379	2380	2381	2382	2383	2384	2385	2386	2387	2388	2389	2390	2391	2392	2393	2394	2395	2396	2397	2398	2399	2400	2401	2402	2403	2404	2405	2406	2407	2408	2409	2410	2411	2412	2413	2414	2415	2416	2417	2418	2419	2420	2421	2422	2423	2424	2425
------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------